

**Dual Voltage  
Shaver Light****994**

These instructions should be read carefully and retained after installation for further reference and maintenance

**Safety Instructions**

- Before installation, maintenance or lamp replacement, ensure that the mains supply to the luminaire is switched off and the circuit supply fuses are removed or circuit breaker turned off.
- It is recommended that a qualified electrician is consulted or used for the installation of this luminaire and installed to the current edition of the IEE wiring regulations.
- This luminaire is only suitable to be installed outside of Zone 2 in a bathroom.
- Check that the total load on the circuit, including this luminaire, does not exceed the rating of the circuit cable, fuse or circuit breaker.
- This luminaire is of Class II construction and does not need to be earthed.

**Installation**

- Remove the two screws from the rear of the luminaire and remove the base.
- Remove the diffuser by squeezing in on it in line with the retaining clips and pulling the diffuser away from the body.
- Remove the lamp from the lampholders.
- Offer the luminaire to the mounting surface and mark out the fixing points.
- Feed the supply cable through the base and terminate the cables into the terminal block, ensuring the correct polarity is observed.
- This luminaire is of Class II construction and does not need to be earthed.
- Return the base to the luminaire and replace the 2 screws removed earlier.
- Offer the luminaire to the mounting surface and fit securely.
- Replace the lamp into the fitting.
- Replace the diffuser, ensuring the retaining clips are properly positioned.

**Lamp Replacement**

- Ensure the power supply to the luminaire is switched off.
- Remove the diffuser as described above.
- Replace the lamp
- Return the diffuser

**Operating Instructions**

- When using the shaver socket, ensure that the shaver plug is fully inserted into the socket and that the Voltage Selection Switch is in the appropriate position.
- The shaver socket is not intended for continuous use or loads exceeding 20VA.
- Turn the light on/off by using the pull cord. This will not affect the operation of the shaver socket.

**Specification**

Power Supply	240V 50Hz	IP Rating	IP20
Shaver Socket Output	Dual Voltage (230V / 115V)	Construction	Class II – Double Insulated
Lamp Type	284mm Striplight	Lamp Wattage	60W Max.



**DETA**  
Kingsway House, Laporte Way  
Luton, Beds, LU4 8RJ, UK  
Tel. +44 1582 544 500 Fax: +44 1582 544 501  
Technical Helpline +44 1582 544 548

