

4 Years
Product Warranty
UK Only

2 Years
On-Site Warranty
Main-land UK Only

Mulu

08222 MUL0105

Kosnic

Mulu EME light & exit sign 1W/5W 6500K

- IP65 LED emergency exit sign bulkhead
- Maintained and non-maintained option
- All legends included
- 20mm Conduit entry
- IP65 and IK10 (vandal resistant) for internal & external uses.
- Dual entry push-wire terminal block for easy loop-in loop-out wiring
- Available in self-test version
- BESA box fitting points



Overview

Mulu LED Emergency Exit Sign or Emergency Bulkhead Luminaire is a self-contained, multi-purpose, non-maintained or maintained 3-hour emergency luminaire solution. It can be used with or without the emergency exit graphics and is supplied with adaptable self-adhesive graphics for escape routes guidance.



General Information

IK Rating	IK10
IP Rating	IP65
Protection Rating	Class II
Installation Area	Internal and External
UEM/EME Protection	Class II

Compliance

LVD	EN 60598-1:2024, EN 60598-2-1:2021, EN 60598-2-22:2022, EN 62471:2008, EN 62493:2015+A1:2022
EMC	EN 55015:2019+A11:2020, EN 61000-3-2:2019+A1:2021, EN 61000-3-3:2013+A1:2019+A2:2021, EN 61547:2023

Technical Summary

Product Code	MUL0105
Emergency Luminous Flux	160 lm
Maintained Luminous Flux	160 lm
Weight	0.5Kg
Dimensions (L x W x D) (mm)	352x110x67
UEM/EME Battery Life	4 y
UEM/EME Input Voltage	220-240Vac 50/60Hz
UEM/EME Ambient Temperature Range	0°C to 40°C
UEM/EME Power Factor	0.58
Emergency Modes	Maintained or Non-maintained
UEM/EME Test Function	Manual
UEM/EME CCT	6,500 K
UEM/EME Input Power (Max)	5 W
UEM/EME Protection	Class II
UEM/EME Dimensions (L x W x D) (mm)	110x352x67
UEM/EME Emergency Operation Test	Manual
Beam Angle - Lumi (°)	120 °

Tel: 01635 523 713

Email: sales@kosnic.com

Kosnic.com



Kosnic Lighting KosnicUK KosnicLightingUK KosnicUK

4 Years
Product Warranty
UK Only

2 Years
On-Site Warranty
Main-land UK Only

Mulu



08222 MUL0105

Accessories

Product Code	Description	Type
KBAT2600LI1	Li-ion Battery Pack, 2600mAh for self test versions of Manot, Mulu, Belum, Kalem, Nitro, Nitro surface, Doxa	Battery
KBAT2000LI1	Li-ion battery 3.7V 2000mAh for self test DD EME	Battery
BAT15NC3	Ni-cd battery SC1500mAh, 3.6V, 55° for MULU	Battery

Overview

Mulu LED Emergency Exit Sign or Emergency Bulkhead Luminaire is a self-contained, multi-purpose, non-maintained or maintained 3-hour emergency luminaire solution. It can be used with or without the emergency exit graphics and is supplied with adaptable self-adhesive graphics for escape routes guidance.



General Information

IK Rating	IK10
IP Rating	IP65
Protection Rating	Class II
Installation Area	Internal and External
UEM/EME Protection	Class II

Tel: 01635 523 713

Email: sales@kosnic.com

Kosnic.com



Kosnic Lighting KosnicUK KosnicLightingUK KosnicUK